



1	Fuse receptacle with standard tab connect, CuSn9 tin plate
2	Fuse holder body, PA 6.6 black
3	Fuse holder cover, clear PC

iMaXX ref.	Description
H1290	fuse holder normOTO, 8 position
H1205	clear cover for H1290
H1281PL	connector key, position 1-2 / A-B
H1282PL	connector key, position 3-4 / C-D
H1283PL	connector key, position 5-6 / E-F
H1284PL	connector key, position 7-8 / G-H
H1291	jumper
H1292	secondary lock
H1299	O-ring for H1290, EPDM, 83mm x 1.1mm

Female connector terminals reference table		
Tyco ref.	Tyco ref.	Wire cross section
Loose	Reeled	mm ²
160773-X	160759-X	0.5 - 1.5 mm ²
341000-X	154717-X	2.5 - 4.0 mm ²
737015-X	790319-X	4.0 - 6.0 mm ²
X = extension for metal alloy options		

Revisions		Date	Appr.
Date	Type		
	Drawn	09/18	GRH
	Checked	09/18	AdH
	Standards		
	Approved	09/18	BE
	Scale	1 : 2	
	Projection		
	Tolerance	± 0.2 mm unless otherwise noted	



Title	H1295 8 pos. normOTO FH
Drawing type	schematic
Drawing number	H1295 drawing 1
Sheet	1 of 1
Layers / Sheet	0 1 2 6 8 9 Sheet 01